32-1208 REV 0120













Page 1 of 5

Series E push / pull force gauges make job task analysis and ergonomics analysis simple and accurate, ideal for workplace design, strength assessment, and ergonomic studies. Series E presents the ergonomist and other professionals with a simple and economical testing solution. 100 lbF, 200 lbF and 500 lbF (500, 2,500, and 5,000 N) capacity force gauges are available, along with a wide range of attachments for various applications.

Select a pre-configured kit, including a gauge, accessories, and carrying case, or select each item individually to suit particular needs.

Features & Specifications

- Measure real time and peak push and pull forces
- Three measuring ranges: 100, 200, and 500 lbF (500, 1000, and 2,500 N)
- Accuracy: ±0.2% of full scale
- Sampling rate: 7,000 Hz
- USB data output
- High / low limit indicators, for pass / fail and minimum force testing
- Averaging mode calculates average force over a period of time
- 5,000-point data memory data points may be saved individually or logged continuously at up to 7,000 Hz. Data points may be bulk downloaded to included MESUR[™] Lite data collection software.
- Statistical calculations for saved data points
- Includes an AC adapter/charger, rechargeable battery, MESUR[™] Lite software, MESUR[™]gauge 90-day trial, USB cable, USB driver, carrying case, and NIST-traceable certificate of calibration with data



Attachments click and lock into place via innovative Click-Lock[™] technology, a rugged anti-rotation locking mechanism. The attachments may be clicked into 90° or 180° orientations. No fastening is required, as with conventional force gauges, reducing the risk of damage to the instrument.



DISA Elektro AG www.disa.ch | info@disa.ch | T: +41 41 666 70 50



Ergonomics Force Gauges Series E

32-1208 REV 0120

Page 2 of 5

Capacities & Resolutions

Model	lbF	ozF	kgF	gF	Ν	kN
ME-100	100 x 0.05	1600 x 1	50 x 0.02	50000 x 20	500 x 0.2	-
ME-200	200 x 0.05	3200 x 1	100 x 0.02	-	1000 x 0.2	1 x 0.0002
ME-500	500 x 0.1	8000 x 2	250 x 0.05	-	2500 x 0.5	2.5 x 0.0005

Force gauges include 110V AC adapters. Add suffix 'E' for Euro plug, 'U' for UK plug, or 'A' for Australian plug.

Ex: ME-100E, ME-200U, ME-500A

Select individual accessories or pre-configured kits



Accessories

Rectangular Pad E1003



Pad dimensions:
4.0 x 1.0 x 0.5 in.
[102 x 25 x 13 mm]

Curved Pad E1004



Pad dimensions:
1.0 in. [25 mm] deep
3.2 in. [81 mm] radius
0.5 in. [13 mm] thick

Square Pad E1002



Pad dimensions:
1.0 x 1.0 x 0.5 in.
[25 x 25 x 13 mm]

Circular Pad E1005



Pad dimensions:
3.0 in. [76 mm] dia.,
0.5 in. [13 mm] thick



DISA Elektro AG www.disa.ch | info@disa.ch | T: +41 41 666 70 50



Ergonomics Force Gauges Series E

32-1208 REV 0120

Snap Hook E1006



- Snap clasp, for added safety
- Swiveling action ensures proper alignment

Chain / Hook Assembly E1007



Single Handle Grip E1008



- Ergonomic rubber-padded handle for a secure grip
- Attaches to force gauge via included thumb screws

Double Handle Grip E1009



- Ergonomic rubber-padded handles, for a secure grip
- Attaches to force gauge via included thumb screws

Pistol Grip E1010



Attaches to force gauge via included thumb screws

Standard Grip Adapter E1011



Adapts other Mark-10 grips via 5/16-18F thread

Page 3 of 5

Includes male/male stud with jam nuts





Ergonomics Force Gauges Series E

32-1208 REV 0120

Looped Cable E1012



- Braided stainless steel
- 43 in. [1,092 mm] length


Myometer Accessory E1013



Includes tabletop mounting kit for force gauge, strap, and mounting screws. Hook not included.

Page 4 of 5





Small Carrying Case E1000



- Shown populated with optional accessories.
- The following page lists the components compatible with each carrying case.

Large Carrying Case E1001



- Shown populated with optional accessories.
- The following page lists the components compatible with each carrying case.





Ergonomics Force Gauges Series E

Page 5 of 5

32-1208 REV 0120

Series EKE Kits - Included Items



	Model No.	Description	Advanced Kits ¹ EKE-100-1 / EKE-200-1 / EKE-500-1	Professional Kits ¹ EKE-100-2 / EKE-200-2 / EKE-500-2	
	ME-100 ME-200 ME-500	Force gauge, 100 lbF / 500 N Force gauge, 200 lbF / 1,000 N Force gauge, 500 lbF / 2,500 N	\checkmark	\checkmark	
1	E1002	Padded attachment, square	×	\checkmark	
6	E1003	Padded attachment, rectangular	\checkmark	\checkmark	
	E1004	Padded attachment, curved	\checkmark	\checkmark	
E	E1005	Padded attachment, circular	×	\checkmark	
-	E1006	Clasp hook	\checkmark	\checkmark	
Concor.	E1007	Chain / clasp hook assembly	×	\checkmark	
	E1008	Single handle grip	×	\checkmark	
	E1009	Double handle grip	\checkmark	\checkmark	
R	E1010	Pistol grip	×	\checkmark	
and the	E1011	Grip adapter	×	×	
2	E1012	Looped cable ²	×	×	
1	E1013	Myometer accessory ²	×	×	
- The	E1000	Carrying case, small	\checkmark	×	
	E1001	Carrying case, large	×	\checkmark	

1. Kits include a force gauge with 110V AC adapter. Add suffix 'E' for Euro plug, 'U' for UK plug, or 'A' for Australian plug. Ex: EKE-100-1E 2. Does not fit into carrying case pockets.



DISA Elektro AG www.disa.ch | info@disa.ch | T: +41 41 666 70 50

